

# KENWOOD

AUDIO VIDEO SURROUND RECEIVER

## KR-200HT

---

### INSTRUCTION MANUAL

KENWOOD CORPORATION

This manual contains instructions for two models. Model availability and features (functions) may differ depending on country and sales area.

# Before applying power

KR-200HT (En/K)

## Before applying power **Caution :** Read this section carefully to ensure safe operation.

Units are designed for operation as follows.

U.S.A. and Canada ..... AC120 V only  
Australia ..... AC 240 V only


Europe and U.K. .... AC 230 V only  
China and Russia ..... AC 220 V only  
\*Other countries ..... AC 110-120/220-240 V switchable

### \*AC voltage selection


The AC voltage selector switch on the rear panel is set to the voltage that prevails in the area to which the unit is shipped. Before connecting the power cord to your AC outlet, make sure that the setting position of this switch matches your line voltage. If not, it must be set to your voltage in accordance with the following direction.

Note:





Our warranty does not cover damage caused by excessive line voltage due to improper setting of the AC voltage selector switch.



## Safety precautions

 **Caution :** Read this section carefully to ensure safe operation.






**WARNING :** TO PREVENT FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS APPLIANCE TO RAIN OR MOISTURE.

 	<b>CAUTION</b> RISK OF ELECTRIC SHOCK DO NOT OPEN	CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER (OR BACK). NO USER-SERVICEABLE PARTS INSIDE, REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.
	THE LIGHTNING FLASH WITH ARROWHEAD SYMBOL, WITHIN AN EQUILATERAL TRIANGLE, IS INTENDED TO ALERT THE USER TO THE PRESENCE OF UNINSULATED "DANGEROUS VOLTAGE" WITHIN THE PRODUCT'S ENCLOSURE THAT MAY BE OF SUFFICIENT MAGNITUDE TO CONSTITUTE A RISK OF ELECTRIC SHOCK TO PERSONS.	
	THE EXCLAMATION POINT WITHIN AN EQUILATERAL TRIANGLE IS INTENDED TO ALERT THE USER TO THE PRESENCE OF IMPORTANT OPERATING AND MAINTENANCE (SERVICING) INSTRUCTIONS IN THE LITERATURE ACCOMPANYING THE APPLIANCE.	

## Unpacking


Unpack the unit carefully and make sure that all accessories are put aside so they will not be lost. Examine the unit for any possibility of shipping damage. If your unit is damaged or fails to operate, notify your dealer immediately. If your unit was shipped to you directly, notify the shipping company without delay. Only the consignee (the person or company receiving the unit) can file a claim against the carrier for shipping damage. We recommend that you retain the original carton and packing materials for use should you transport or ship the unit in the future.

### Accessories

FM indoor antenna (1) 	AM loop antenna (1) 	Loop antenna stand (1) 
Remote control unit (1) 	Batteries (R6/AA) (2) 	

# Special features

## DOLBY PRO LOGIC & DOLBY 3 STEREO

The surround system reproduces video software programs carrying the  mark with similar acoustic effects to movie theaters.

The DOLBY PRO LOGIC mode controls the audio signals of the Front Left/Right, Center and Rear surround channels using the built-in directivity enhancer circuit to reproduce the feeling of sound motions very realistically.




The DOLBY 3 STEREO mode can reproduce the motions of sound even when only the front and center speakers are used, by providing proper acoustic position using the directivity enhancer circuit.

## SRS 3D Stereo

The SRS (Sound Retrieval System) is an innovative system simulating a 3-dimensional sound space, which features clearly improved feelings of depth, sound field extension and acoustic image positioning as well as a widened listening area.

# Contents

Caution : Read the pages marked  carefully to ensure safe operation.

<b>Before applying power</b> .....	<b>2</b>
 Before applying power .....	2
 Safety precautions .....	2
<b>Special features</b> .....	<b>3</b>
<b>System connection</b> .....	<b>4</b>
Connections of Audio and Video components .....	4
About the system control connections .....	5
Connections of speakers .....	6
Connections of antenna .....	7
FM DE-EMPHASIS/CHANNEL SPACE switch .....	8
<b>Controls and indicators</b> .....	<b>9</b>
<b>Operation of remote control unit</b> .....	<b>10</b>
<b>Playing music</b> .....	<b>12</b>
<b>Sound adjustment functions</b> .....	<b>13</b>
<b>Recording</b> .....	<b>16</b>
<b>Broadcast Reception</b> .....	<b>17</b>
Receiving broadcast stations .....	17
Receiving radio stations by specifying its frequency .....	18
Storing radio stations in memory (Station preset) .....	19
Receiving a preset station .....	19
Receiving all preset stations in order (PCALL) .....	19
<b>Operation of video components</b> .....	<b>20</b>
Playback of videotape .....	20
Recording of video source (VIDEO2 → VIDEO1) .....	20
<b>Presence play</b> .....	<b>21</b>
Adjustments for surround play .....	22
Surround play .....	24
SRS 3D Stereo (Sound Retrieval System) .....	25
<b>In case of difficulty</b> .....	<b>26</b>
 <b>Specifications</b> .....	<b>28</b>

# System connection

KR-200HT (En/K)

## Connections of Audio and Video components

Make connection as shown below.


When connecting the related system components, refer also to the instruction manuals of the related components.

⚠ Do not plug in the power lead until all connections are completed.

### Malfunction of microcomputer

If operation is not possible or erroneous display appears even though all connections have been made properly, reset the microcomputer referring to "In case of difficulty".

- 26 -



# About the system control connections

Connecting system control cords after connecting a KENWOOD audio component system lets you take advantage of convenient system control operations.

There are two KENWOOD system control modes. Make connections according to the groups of terminal symbols shown below.


**[XS8] Mode:** lets you combine **[XR]**, **[XS]**, and **[XS8]** terminals

**[SL16] Mode:** for **[SL16]** terminals only

This unit is compatible with both **[XS8]** and **[SL16]** modes. It comes from the factory set to the **[SL16]** mode. To switch to the **[XS8]** mode, follow the instructions in "SWITCHING BETWEEN **[XS8]** AND **[SL16]**" below.


## EXAMPLE: **[XS8]** mode connections

The underlined portion represents the setting of the system control mode.



## EXAMPLE: **[SL16]** mode connections


The underlined portion represents the setting of the system control mode.



- Some CD players and cassette decks are not compatible with the **[SL16]** system control mode. Be sure to use the **[XS8]** system control mode when making system connections with equipment that is not **[SL16]** compatible.
- Some MD players are not system control compatible. You cannot make system control connections to this kind of equipment.



1. **[SL16]** equipment cannot be combined with **[XR]**, **[XS]**, and **[XS8]** equipment for system operations. If your equipment consists of this kind of combination, please do not connect any system control cords. Even without system control cords, normal operations can be carried out without affecting performance.
2. Do not connect system control cords to any components other than those specified by KENWOOD. It may cause a malfunction and damage your equipment.
3. Be sure the system control plugs are inserted all the way in to the system control terminals.



## ABOUT THE SYSTEM CONTROL OPERATIONS

**Remote Control** (possible when the system control mode matches):

Lets you operate source components with the system remote supplied with this unit.

**Automatic Operation** (Except **[XR]** equipment)

When you start playback from a source component, the input selector on this unit switches to that component automatically. (Except TAPE 2)


**Synchronized Recording** (Except **[XR]** equipment)

Lets you synchronize recording with the start of playback when recording from CD, MD.

## SWITCHING BETWEEN **[XS8]** AND **[SL16]**

The system control mode can be switched over easily with the following operation.

- ① Unplug the AC power cord from the wall outlet.
- ② Set the SYSTEM CONTROL switch on the rear panel to the desired position.




- This operation does not affect the items stored in memory.



1. Connect all cords firmly. If connections are loose, there could be loss of sound or noise produced.
2. When plugging and unplugging connection cords, be sure to first remove the power cord from the AC outlet. Plugging / unplugging connection cords without removal of the power cord can cause malfunctions or damage to the unit.
3. Do not connect up a power source which is larger than that indicated on the socket at the rear of the unit.
4. If the system control cords or audio cords are not connected properly, the remote control or automatic operation between system components will not work properly.

# Connection of speakers



- Never short-circuit the + and - speaker cords. For the symptom and remedy when a speaker cord is shorted.
- If the left and right speakers are connected inversely or if the speaker cords are connected with reversed polarity, the sound becomes unnatural with ambiguous acoustic image positioning. Be sure to connect the speakers and speaker cords correctly.
- Connect a sub woofer if you want to enhance the bass sound. The connected sub-woofer should be a power sub-woofer with a built-in amp.

# Connection of antenna

## Connection method to each antenna terminal



① Push lever.



② Insert cord.




③ Return lever.



## AM loop antenna connection

The supplied antenna is for indoor use. Place it as far as possible from the main system, TV set, speaker cords and power cord, and set it to a direction which provides the best reception.




## FM indoor antenna connection

The accessory antenna is for temporary indoor use only. For stable signal reception we recommend using an outdoor antenna. Remove the indoor antenna if you connect one outdoors.

## FM outdoor antenna connection


Lead the 75  $\Omega$  coaxial cable connected to the FM outdoor antenna into the room and connect it to the FM 75  $\Omega$  terminal.



### **FM DE-EMPHASIS / CHANNEL SPACE switch (Except for U.S.A. and Canada)**

The FM DE-EMPHASIS / CHANNEL SPACE switch on the rear panel is set to the correct setting that prevails in the area to which the unit is shipped. However, if the FM DE-EMPHASIS / CHANNEL SPACE setting is not matched to the area where the unit is to be used; for instance, when you moved from area 1 to area 2 or vice versa, desired reception of AM / FM broadcasts is not expected. In this case, change the FM DE-EMPHASIS / CHANNEL SPACE setting in accordance with the area corresponding to the table. The FM DE-EMPHASIS is switched over at the same time.

- When changing the setting of the FM DE-EMPHASIS / CHANNEL SPACE switch, first disconnect the power cord of the amplifier, then reset the channel space switch, connect the power cord again, and turn the power on.




	Area	CHANNEL SPACE freq.	FM DE-EMPHASIS
1	U.S.A., Canada, Hawaii, South American countries	FM: 100kHz AM: 10kHz	75 µs
2	Other countries	FM: 50kHz AM: 9kHz	50 µs



# Controls and indicators

KR-200HT (En/K)



## 1 POWER key

Press to switch the power ON and OFF.

## 2 STANDBY indicator

## 3 SRS 3D indicator

Lights when the SRS 3D system is ON.

## 4 SPEAKERS indicator

Lights when the speakers are ON.

## 5 STEREO key

Press to turn the surround mode OFF. - 24

## 6 DOLBY PRO LOGIC key

- 22

## 7 DOLBY 3 STEREO key

- 24

## 8 SRS 3D key

- 25

## 9 INPUT SELECTOR knob

Rotate to select the input source.

## 10 VOLUME CONTROL knob

## 11 PHONES jack

Plug headphones into this jack.

## 12 AUTO key

Press to select the tuning mode from the auto tuning and manual tuning modes. - 17

Press and hold the **AUTO** key for more than 2 seconds to switch the VIDEO1 display to another input display. - 12

## 13 SPEAKERS key

Press to turn the speakers ON and OFF.

## 14 DIRECT key

Press when tuning a broadcast station by entering the digits of its frequencies. - 18

## 15 MEMORY key

Press when registering a broadcast station in the preset memory. - 19

## 16 Numeric keys (1 to 0, +10)

## 17 BAND key

Press to switch the broadcasting band. - 17

## 18 DISPLAY key

Press to switch the displayed information between the surround mode display and input selector display.

Press and hold the **DISPLAY** key for more than 2 seconds to switch the display brightness.

## 19 TUNING keys (V, ^)

Press to select a radio station. - 17

## 20 TAPE 2 MONITOR key

Press to monitor the sound being recorded, etc. - 16

## 21 N.B. key

Press to compensate for the insufficiency in the base sound. - 14

## 22 P.CALL keys (V, ^)

Press to select one of the preset stations. - 19

## 23 SOURCE DIRECT key

Press to listen to the source sound with a higher sound quality. - 14

## About the STANDBY indicator

This unit has a **STANDBY** indicator, the lighting of which indicates that a small amount of current is supplied to back up the internal memory of the unit. This status is referred to as the standby mode of the unit. In this mode, the power of the unit can be switched ON from the remote control unit. When the unit is not to be used for a long period of time, plug the power cord from the power outlet.

# Operation of remote control unit

KR-200HT [En/K]

## Names of keys and their functions

The remote control unit provided with the receiver can also control KENWOOD cassette decks, MULTIPLE CD player and MD recorder connected to the receiver through system control cords. For details of the controllable functions, refer to the instruction manuals of these components.

Model: RC-R0505  
Infrared ray system

### Numeric keys

Used as the numeric keys of the input source component being selected.

### INPUT keys

Press to select the input.



The **AV AUX** key cannot be used with the KR-200HT.

### CENTER MODE key

- 22

Press to select the center mode in the DOLBY PRO LOGIC surround mode.

### SETUP key

- 13 - 22

Press to set up the balance or surround play.

### LEVEL CONTROL keys

- 13 - 22

Press to adjust the tone or during setup of the surround mode.

### POWER key

Press to switch ON/OFF the power of this unit as well as the KENWOOD components connected to it through system control cords.

Refer to the remote control key correspondence table on the next page.

### MUTE key

Press to mute sound temporarily.

### VOLUME CONTROL keys

Press to adjust the volume.

### LISTEN MODE key


- 24

Press to select the type of the surround mode.

### SOUND key


- 13 - 25

Press to adjust the tone.




## Loading batteries

① Remove the cover.




② Insert batteries.



● Insert two AA-size (R6 / SUM-3) batteries as indicated by the polarity marking.

③ Close the cover.






















# Operation procedure


- 1** Switch ON the power of the main unit.
- 2** Select the component to be remote controlled with one of the controlled component selection keys.
- 3** Refer to the remote control key correspondence table below and press the key for the desired operation.

- Pressing the **POWER** key of the remote control unit while the **STANDBY** indicator is lit turns the power ON. Press the desired key after the power has been turned ON.
- When two operation keys of the remote control unit are pressed successively, press each key securely reserving an interval of more than 1 second for each press.

**Remote control key correspondence table (For KENWOOD component control mode)**

Controlled component selection key Operation key	TUNER	CD	TAPE1	*1 TAPE1 (When used with a MD)
 P.CALL	<b>P.CALL keys</b> Recalls preset stations.	 (Skip key)	—	 (Skip key)
 AUTO	<b>AUTO key</b> Press to select the auto tuning mode.	 (Stop key)	 (Stop key)	 (Stop key)
 DISK SKIP A/B +100	—	<b>DISC SKIP key</b> Press to select the disc to be played.	<b>A/B key</b> Select TAPE A or B.	<b>+100</b>
 BAND	<b>BAND key</b> Press to switch the broadcast band.	 (Play/pause key)	 (Forward play key)	 (Play key)
	 (Tuning keys) Press to tune broadcast stations.	 (Search key)	 (Search key)	 (Search key)
	—	—	 (Reverse play key)	—

## Approximate operating range



**Model: RC-R0505**  
**Infrared ray system**

- \*1: No remote control key is marked MD, but the **TAPE1** key can be used to control a MD player by switching the display of the main unit from VIDEO1 to TAPE1 then to MD.

— 12 —






1. The supplied batteries are intended for use in operation checks. Therefore, their lives may be shorter than ordinary batteries.
2. When the remote-controllable distance gets shorter than before, replace both batteries with new ones.
3. Malfunction may occur if direct sunlight or the light of a high-frequency lighting fluorescent lamp enters the remote control light

# Playing music


KR-200HT (En/K)

2




 : Keys or controls to be used in this operation

## 1 Turn the power ON.



## 2 Select the **SPEAKERS** key setting.




### When the **SPEAKERS** indicator is ON:

The speakers connected to the **SPEAKERS** terminals on the rear panel output sound.

### When the **SPEAKERS** indicator is OFF:

The speakers do not output sound. Use this setting when listening through headphones.

## 3 Select the input source.



The input sources are switched in the following order:

- ① **TUNER** (frequency display)
- ② **PHONO**
- ③ **VIDEO1** (TAPE1 or MD)\*1
- ④ **CD**
- ⑤ **VIDEO2**

The selected source is displayed



### \*1: Switching the **VIDEO1** display to **TAPE1** or **MD** display

When a KENWOOD cassette deck or MD recorder is connected in the [SL16] system control mode, the VIDEO 1 input should be switched to the TAPE1 or MD input with the following operation.


- ① Select **VIDEO1** with the **INPUT SELECTOR**.
- ② Press and hold the **AUTO** key for more than 2 seconds to select **TAPE1** or **MD**.




- ① **VIDEO1** → ② **TAPE1** → ③ **MD**

## 4 Play the selected source.

## 5 Adjust the volume.





Volume level is displayed.



- The time taken till volume level is displayed is variable depending on the current operating condition.
- Rotating the **VOLUME CONTROL** at a higher speed increases the amount of volume change (AI VOLUME function).
- The sound of input source cannot be listened to while **TAPE 2 MONITOR** is ON.

# Sound adjustment functions

KR-200HT (En/K)



: Keys or controls to be used in this operation

## Adjusting the tone

① Ensure that the SRS 3D and S.DIRECT indicators are not lit.


② Select the tone mode to be adjusted (from BASS, MIDDLE and TREBLE).



③ Adjust the tone



To increase level  
To decrease level



The level can be adjusted between -8 and +8 with an increment or decrement of 2 per press.



Make sure that the light is out.

- If the S.DIRECT indicator is lit, press the **S.DIRECT** key to turn it off.
- If the SRS 3D indicator is lit, press the **SRS 3D** key to turn it off.

Each press of the key switches the modes as follows:  
(When the SRS 3D Stereo is OFF)

- ① **BASS** : Mode for adjusting the low frequencies.
- ② **MIDDLE** : Mode for adjusting the middle frequencies.
- ③ **TREBLE** : Mode for adjusting the high frequencies.
- ④ End of setting

- Adjustments of SRS (Sound Retrieval System) 3D Stereo

→ 25

BASS +2

Display when "BASS" is selected.


The displayed value changes.

BASS -2

## Adjusting the left/right sound balance

① Ensure that the SURROUND, 3 STEREO and S.DIRECT indicators are off.

② Press the SETUP key.




③ Adjust the balance.



To decrease the left channel sound

To decrease the right channel sound



④ Press the SETUP key to return to the previous input selector display.



SURROUND 3 STEREO S.DIRECT


Make sure that the light is out.

- If the SURROUND, 3STEREO or S.DIRECT indicators are lit, press the **STEREO** key to turn them OFF.



Position of the left speaker


Indicates the center

Position of the right speaker





Indicates the balance setting



 Keys or controls to be used in this operation

## Source Direct playback


This feature allows you to play the source signal with a high quality by passing it only through the minimum required circuitry.



- During Source Direct playback, the tone controls (BASS, MIDDLE and TREBLE), balance control and N.B. are defeated.
- The Source Direct playback is canceled when any key associated with the surround play is pressed.



### To cancel

Press the SOURCE DIRECT key again.



## Compensating for low frequencies (N.B.: Natural Bass circuit)


N.B. circuit is used to compensate for the low frequencies which are less audible during low-volume listening.






- When the S.DIRECT is selected, the N.B. control keys are not effective.

### To cancel

Press the N.B. key again.






 Keys or controls to be used in this operation

## To listen through headphones




① Press the SPEAKERS key to OFF.



② Plug headphones.





③ Adjust the volume.



## To mute sound temporarily

Remote control unit only



**To cancel**  
Press the MUTE key again.

# Recording


KR-200HT (En/K)

When recording sound with a recorder component of KENWOOD, synchro recording is possible by setting the INPUT SELECTOR to select TAPE1 or MD according to the connected component.

## Preparation

- Switch the VIDEO1 display to TAPE1 or MD with the following operation.
- ① Select VIDEO1 with the INPUT SELECTOR.
- ② Press and hold the AUTO key for more than 2 seconds.

Each press switches the display.




## To record a music source

- ① Select the source to be recorded.



INPUT SELECTOR



Select an input source other than TAPE 1.

- ② Put the cassette deck in record-pause mode.

- ③ Play the source and start recording.


The input sources are switched in the following order:

- ① TUNER (frequency display)
- ② PHONO
- ③ VIDEO1 (TAPE1 or MD)
- ④ CD
- ⑤ VIDEO2

- The VIDEO1 display can be switched to the display of other input by using the procedure described in "Preparation" above.
- For MD recording, refer to the instruction manual of your MD recorder.
- It is not possible the VIDEO1 or MD input to TAPE1 because all of these components should use the same INPUT SELECTOR position.

## Copying tape (Tape dubbing TAPE 2 → TAPE 1)

- ① Press the TAPE 2 MONITOR key.





BAND DISPLAY TUNING TAPE2 MONITOR




- ② Select a source other than TAPE 1.

INPUT SELECTOR



- ③ Play cassette deck 2 and start recording on cassette deck 1.



- For copying a tape using a double cassette deck, read the instruction manual of the double cassette deck.

## Copying tape (Tape dubbing TAPE 1 → TAPE 2)

- ① Select TAPE 1 with the INPUT SELECTOR control of the main unit.
- ② Play the cassette deck connected to the TAPE 1 jacks and start recording of the cassette deck connected to the TAPE 2 jacks.


## Regarding TAPE 2 MONITOR

A cassette deck or graphic equalizer can be connected to this unit's TAPE 2 MONITOR terminals. If you connect a graphic equalizer, turn the TAPE 2 MONITOR key ON. If you connect a 3-head cassette deck, you can monitor the source sound, or the sound being recorded, while recording. Pressing the TAPE 2 MONITOR key lets you compare the recorded sound and the source sound. Refer to the operating manual for the component you connected for further details.



# Broadcast reception


KR-200HT (En/K)



: Keys or controls to be used in this operation


## Receiving broadcast stations

### 1 Select the TUNER input.



The input sources are switched in the following order:


- ① TUNER (frequency display)
- ② PHONO
- ③ VIDEO1 (TAPE1 or MD)\*1
- ④ CD
- ⑤ VIDEO2



- The last frequency tuned before is displayed.
- \*1: How to switch the display


- 16 - 12

### 2 Select the broadcast band.




Each press switches the band as follows:

- ① FM
- ② AM




"AM" or "FM" indicator

### 3 Select the tuning method.





Each press switches the tuning method as follows:

- ① AUTO lit (auto tuning)
- ② AUTO not lit (manual tuning)



- Usually, set the switch to **AUTO** (auto tuning).  
Select manual tuning when noise interferes due to weak radio wave.  
(The stereo broadcasting is received in monaural during manual tuning.)



### 4 Select a station.




"TUNED" lights up when a station is tuned.

Auto tuning : The next station found is tuned automatically.  
Manual tuning : Press repeatedly or hold until a station is tuned.


- The same operation is also available with the and keys of the remote control unit.



 : Keys or controls to be used in this operation


## Receiving radio stations by specifying its frequency

### 1 Select the TUNER input.




The input sources are switched in the following order:

- ① TUNER (frequency display)
- ② PHONO
- ③ VIDEO1 (TAPE1 or MD)
- ④ CD
- ⑤ VIDEO2




### 2 Select the broadcast band.





Each press switches the band as follows:

- ① FM
- ② AM



"AM" or "FM" indicator

### 3 Specify the frequency.



Press the numeric keys according to the frequency to be tuned as shown below.


\*AM10kHz/FM100kHz territories (U.S.A., Canada, etc.)

AM 810 kHz	8	1	( 10 kHz space)
AM 1260 kHz	1	2	6 ( 10 kHz space)
FM 89 MHz	8	9	0 (100 kHz space)
FM 92.5 MHz	9	2	5 (100 kHz space)

\*AM9kHz/FM50kHz territories (other countries)

AM 810 kHz	8	1	0 ( 9 kHz space)
AM 1260 kHz	1	2	6 0 ( 9 kHz space)
FM 89 MHz	8	9	0 0 ( 50 kHz space)
FM 92.5 MHz	9	2	5 0 ( 50 kHz space)

\*FM DE-EMPHASIS/CHANNEL SPACE switch





"TUNED" lights up when a station is tuned.

● If you make a mistake, the frequency display blinks for a few seconds. In this case, repeat step 3 from the beginning.

## Preparation

- Select the **TUNER** input.




 : Keys or controls to be used in this operation

## Storing radio stations in memory (Station preset)

- Select the receiving band.
- Select a station or frequency.
- Press the **MEMORY** key during receiving a station.




**AUTO DIRECT MEMORY**



**Proceed to step ④ within 5 sec.**


(If more than 5 sec. have elapsed, press the **MEMORY** key again.)

- Select one of the preset numbers from 1 to 30.



Lights up (for 5 sec.)

Lights up (for 5 sec.)



Press the numeric keys in the following order.


To store in "15" ... **+10**, **5**

To store in "20" ... **+10**, **+10**, **0**

- Repeat steps ① ~ ③ for each of the stations to be stored in memory.
- If a station is stored in a preset number which has already stored a station memory under it, the previous memory is replaced by the new memory content.

## Receiving a preset station

Press the preset number of the desired station.




Press the numeric keys in the following order.

To recall "15" ... **+10**, **5**

To recall "20" ... **+10**, **+10**, **0**

- If you make a mistake in entering the figure of 10, press the **+10** key repeatedly until the original display is shown, then enter the correct number.

Preset number stored in memory



## Receiving all preset stations in order (P. CALL)



The preset number increases.



The preset number decreases.

- Every time the key is pressed, the next station in the order of the preset number is received.

When you press **P. CALL** key, ..... 1 → 2 → 3 ..... 28 → 29 → 30

When you press **P. CALL** key, ..... 1 → 2 → 3 ..... 28 → 29 → 30

If the key is held pressed ..... Preset stations will be received successively for about half a second each.



- The same operation is also available with the **P. CALL** keys of the main unit.


# Operation of video components

KR-200HT (En/K)

For the connections and operations, also read carefully the instruction manuals of the video components.

→ 4




 : Keys or controls to be used in this operation

## Playback of videotape

**1** Turn the power of the monitor TV ON.


**2** Select the VIDEO1 or VIDEO2 input.



The input sources are switched in the following order:

- 1 TUNER (frequency display)
- 2 PHONO
- 3 VIDEO1 (TAPE1 or MD)\*1
- 4 CD
- 5 VIDEO2

"VIDEO1" or "VIDEO2" should be displayed.



• Select the input to which a video deck is connected.

• \*1: How to switch the display

→ 12 → 16


• For the operations of the monitor TV and video deck, refer to their instruction manuals.

**3** Play the video deck.

## Recording of video source (VIDEO 2 → VIDEO 1)

**1** Connect the video source component to be played.

**2** Select the VIDEO 2 input.




- Connect the component to be played to the VIDEO 2 jacks.
- The connectable components include a video deck (playback only), video camera (playback only), LD player or DBS tuner.

The input sources are switched in the following order:

- 1 TUNER (frequency display)
- 2 PHONO
- 3 VIDEO1 (TAPE1 or MD)
- 4 CD
- 5 VIDEO2

"VIDEO2" should be displayed.



**3** Play the source component.

**4** Start recording on the recording video deck.

• Start recording with the video deck which is connected to the VIDEO 1 jacks.


# Presence play

KR-200HT (En/K)

The surround modes allow you to enjoy the feeling of presence in music. Select the mode according to the source or components played. For the connections of the surround and/or center speakers, refer to "Connection of speakers".


- 6 -

## DOLBY PRO LOGIC surround mode


Video, DVD and LD software programs carrying the  mark contain recording of the same Dolby Surround data as those used in movie theaters.

The DOLBY PRO LOGIC surround mode uses the Dolby Surround data and brings into home a similar sound field with full of presence to movie theatres.

To use this mode, connect the surround (and center) speakers.



In case center speaker is not used




## DOLBY 3 STEREO mode

If the left and right speakers are installed apart from each other, the center acoustic image (words, etc.) may vary depending on the listener's position. The DOLBY 3 STEREO mode provides an improved positioning of the center acoustic image regardless of the listening position.

Use this mode when playing videotape, DVD or LD software carrying the  mark.

To use this mode, connect the center speaker.





## Recommended speaker installation



It is recommended that the surround speakers are installed straight to the left and right of the listening position or slightly behind, at a height of about 1 meter higher than the listener's ears. Each surround speaker should be installed so that the longer sides are horizontal.

To improve the feeling of presence in the surround modes, various parameters of each surround mode can be set up according to the speaker system used as well as to the environmental of the listening room. The following procedure let you set the parameters of the surround mode (DOLBY PRO LOGIC, DOLBY 3 STEREO).


Once the settings have been done, it is held in memory so re-adjustment is not necessary even after the mode has been changed to other modes.




: Keys or controls to be used in this operation

## Adjustments for surround play


### 1 Select the DOLBY PRO LOGIC surround mode.



- Select a surround mode according to the played source and your system components.




### 2 Select the CENTER MODE.



- Each press of **CENTER MODE** key switches the modes as follows:
- ① **NORMAL** : When the center speaker is a compact speaker.
  - ② **WIDEBAND** : When the center speaker is a large speaker.
  - ③ **PHANTOM** : When no center speaker is used.


### 3 Adjust the front speaker balance.



Adjustment procedure: Each press of the **SETUP** key switches the adjusted items as shown below.


- ③ Adjusting the front speaker balance
- ④ Adjusting the volume level of each speaker
- ⑤ Adjusting the delay time
- End of setup

To cancel setup in the middle, press the **SETUP** key repeatedly until the setup mode is cancelled.




## How to calculate the proper delay time

Assuming that the distance from the front speakers is A meters and that from the surround speakers is B meters:



### ① Use the delay time calculation chart on the right.

Example:  
When A = 3 m, B = 3 m,  
the delay time is 20 ms.



### ② Use the following formula for calculation.

Delay time =  
 $20 + 3 \times (A - B)$  (Unit: ms)

## What is delay time?




The sound entering the ears include the direct sound coming from the sound source and the indirect sounds reflected from the walls, floor, ceiling, etc. The indirect sounds are delayed because they travel longer distance required for reflection before they reach the ears. The delay time is the difference in time between the direct sound and indirect sounds.

## 4 Adjust the volume level of each speaker.


① Ensure that "TEST L" is displayed. Test tone will be output from each speaker.

② Adjust the volume levels of the center speaker and surround speakers with reference to the front speaker (left & right) levels.

(1) While test tone is output from the speaker(s) to be adjusted,  
(2) Adjust the speaker level.



③ After having adjusted all of the speaker levels, establish the setup.



After this, the unit enters the condition for "⑤ Adjust the delay time".

• Noise-like test tone moves across speakers at intervals of 1.5 seconds.

TEST L (Front speaker, left)


TEST C (Center speaker)

(Only when **NORMAL** or **WIDE BAND** is selected in step ②)

TEST R (Front speaker, right)

TEST S (Surround speakers)

(Only when **PRO LOGIC** is selected in step ①)



Display when test tone is output from surround speakers

• Be sure to adjust from the listening position.

• Each press of a **LEVEL CONTROL** key varies the level by 1 dB.

• The volume level can be adjusted in the range from -10 to +10 dB.


• The front speaker (left & right) levels cannot be varied with the **LEVEL CONTROL** keys.

• Adjust the volume level from each of the center speaker and surround speakers while test tone is output from the corresponding speaker.

## 5 Adjust the delay time.

① Ensure that the delay time adjustment display is displayed.

② Adjust the delay time.



③ Establish the setup.




This is the end of setup (the unit returns to the condition before starting the setup operations).

• Check the proper delay time for your listening room by referring to "How to calculate the proper delay time".

• Select an integer value which is closest to the value obtained with "How to calculate the proper delay time".

• The delay time can be adjusted to 15, 20, 25 or 30 ms.



Adjustment position

Front speaker side


Surround speaker side

Delay time

When playing videotape (DVD or LD) software carrying the **DOLBY SURROUND** mark, a sound field with enhanced surround effects can be enjoyed by using the DOLBY PRO LOGIC or DOLBY 3 STEREO mode.

Be sure to complete "Adjustments for surround play" prior to starting playback in one of these surround modes.


- 22 -



Keys or controls to be used in this operation

## Surround play


### 1 Select one of the surround modes.



Each press of **LISTEN MODE** key switches the modes as follows.

- ① STEREO
- ② PRO LOGIC
- ③ 3 STEREO

• The surround modes can also be selected directly using the corresponding keys on the main unit.




Example when **DOLBY PRO LOGIC** is selected

### 2 Play a video software program.


### 3 Adjust the volume.

## To cancel the SURROUND play



On the remote control unit, the following modes are switched every time the **LISTEN MODE** key is pressed.

- ① STEREO
- ② PRO LOGIC
- ③ 3 STEREO






Manufactured under licence from Dolby Laboratories Licensing Corporation.

"Dolby", "Pro Logic" and the double - D symbol are trademarks of Dolby Laboratories Licensing Corporation.



The Sound Retrieval System is an epochal system which produces a three-dimensional sound space by applying the most suitable processing to the sound signal on the basis of the human listening mechanism. This permits real depth and sound location, considered as difficult to realize with conventional 2-channel stereo (general stereo). A sufficient effect can be obtained for any source (CD, tape, broadcasts, etc.).



 : Keys or controls to be used in this operation

## SRS 3D Stereo (Sound Retrieval System)

### Adjusting the tone.

- ① Ensure that the S.DIRECT indicator is not lit.



- ② Turn the SRS 3D stereo ON.



- ③ Adjust the effect strength (level).


- (1) "CENTER" or "SPACE" should be displayed.



Increasing the "CENTER" level enhances the feeling of depth around the center.


Increasing the "SPACE" level makes the sound expansion wider.

- (2) Adjust the level.




Each press of the key switches the modes as follows:



- ① SRS 3D is lit  
..... SRS 3D STEREO ON  
② SRS 3D is not lit  
..... SRS 3D STEREO OFF



Each press of the key switches the modes as follows:

- ① **CENTER** : Mode for adjusting the depth of SRS 3D.  
② **SPACE** : Mode for adjusting the expansion of SRS 3D.  
③ End of setting

- The BASS, MIDDLE and TREBLE adjustments are not available while the SRS 3D Stereo is ON. For the BASS, MIDDLE and TREBLE adjustment procedures: 



- Adjustment is possible in the range from 1~7.  
● Please set as desired according to the titles being played back etc.

Even if the sound is recorded while the SRS 3D stereo effect is applied, the effect is not recorded together with the source sound.

# In case of difficulty

KR-200HT (En/K)

What appears to be a malfunction may not always be serious. If your unit should not perform as expected, consult the table below to see if the problem can be corrected before seeking help from your dealer or service representative.

## Operation to reset

The microcomputer may fall into malfunction (impossibility to operate, erroneous display, etc.) when the power cord is unplugged while power is ON or due to an external factor. In this case, execute the following procedure to reset the microcomputer and return it to normal condition.

1. Unplug the AC power plug from the wall outlet.
2. While holding the POWER switch depressed, plug the AC plug into the power outlet.

● Please note that resetting the microcomputer clears the contents stored in and returns to the condition when it left the factory.

## Amplifier

Symptom	Cause	Remedy
Sound is not output or the volume level is low.	<ul style="list-style-type: none"> <li>● The speaker cords are disconnected.</li> <li>● MUTE is ON. (The MUTE ON indicator is blinking)</li> <li>● The <b>SPEAKERS</b> keys are set to OFF.</li> <li>● The <b>TAPE 2 MONITOR</b> key is set to ON.</li> </ul>	<ul style="list-style-type: none"> <li>● Connect them properly referring to "Connection of speakers". - 6</li> <li>● Press the <b>MUTE</b> key to OFF. - 15</li> <li>● Set the <b>SPEAKERS</b> key to ON. - 12</li> <li>● Set the <b>TAPE 2 MONITOR</b> key to OFF. Set the input selector to the position other than tuner.</li> </ul>
The <b>STANDBY</b> indicator blinks and sound is not output.	<ul style="list-style-type: none"> <li>● Speaker cords are short-circuited.</li> </ul>	<ul style="list-style-type: none"> <li>● Turn the power off, eliminate the short-circuiting, then turn on the power again. - 6</li> </ul>
Sound is not output from one of the speakers.	<ul style="list-style-type: none"> <li>● The speaker cord is disconnected.</li> <li>● The <b>BALANCE</b> control is set to an extreme position.</li> </ul>	<ul style="list-style-type: none"> <li>● Connect it properly referring to "Connection of speakers". - 6</li> <li>● Adjust the Left/Right balance. - 13</li> </ul>
Sound is not output from the surround speaker and/or center speaker, or their sound is very small.	<ul style="list-style-type: none"> <li>● The surround speaker cords and/or center speaker cord are disconnected.</li> <li>● The Surround play mode has not been engaged.</li> <li>● The surround and center speaker levels are set to the minimum positions.</li> </ul>	<ul style="list-style-type: none"> <li>● Connect them properly referring to "Connection of speakers". - 6</li> <li>● Set the presence mode. - 22</li> <li>● Adjust the surround and center speaker levels.</li> </ul>
A hum noise is generated when the <b>PHONO</b> input is selected.	<ul style="list-style-type: none"> <li>● The audio cord from the turntable is not inserted securely into the <b>PHONO</b> jacks.</li> <li>● The turntable is not grounded.</li> </ul>	<ul style="list-style-type: none"> <li>● Insert the audio cord plugs securely into the <b>PHONO</b> jacks. - 4</li> <li>● Connect the grounding wire to the GND terminal on the rear panel.</li> </ul>
System control is not available when <b>TAPE 1</b> or <b>MD</b> is selected.	<ul style="list-style-type: none"> <li>● "TAPE 1" or "MD" is not displayed.</li> </ul>	<ul style="list-style-type: none"> <li>● Switch the display to <b>TAPE 1</b> or <b>MD</b>. - 12, - 16</li> </ul>
System control is not available.	<ul style="list-style-type: none"> <li>● The <b>XS8</b> and <b>SL16</b> modes were switched while the AC plug is left plugged into the wall power outlet</li> </ul>	<ul style="list-style-type: none"> <li>● Unplug the AC plug from the wall outlet and switch the <b>XS8</b> or <b>SL16</b> mode as required. - 5</li> </ul>
Display is dimly lit.	<ul style="list-style-type: none"> <li>● The setting is not correct.</li> </ul>	<ul style="list-style-type: none"> <li>● Adjust the brightness with the <b>DISPLAY</b> key. - 9</li> </ul>

## Tuner

Symptom	Cause	Remedy
Radio stations cannot be received.	<ul style="list-style-type: none"> <li>● No antenna is connected.</li> <li>● The broadcast band is not set properly.</li> <li>● The frequency of the desired station is not tuned.</li> </ul>	<ul style="list-style-type: none"> <li>● Connect an antenna. - 7</li> <li>● Set the broadcast band properly. - 17</li> <li>● Tune the frequency of the desired station. - 17</li> </ul>
Interference.	<ul style="list-style-type: none"> <li>● Noise due to ignition noise of an automobile.</li> <li>● Noise due to an influence from an electric appliance.</li> <li>● Noise due to a nearby TV set.</li> </ul>	<ul style="list-style-type: none"> <li>● Install the outdoor antenna away from the road.</li> <li>● Turn off the power to the appliance.</li> <li>● Install the system farther away from the TV set.</li> </ul>
A station which was preset cannot be received by pressing the corresponding numeric key.	<ul style="list-style-type: none"> <li>● The preset station belongs to a frequency that cannot be received.</li> <li>● The preset memory was cleared because the power cord had been unplugged for a long period of time.</li> <li>● The <b>TUNER</b> input is not selected.</li> </ul>	<ul style="list-style-type: none"> <li>● Preset a station with a receivable frequency. - 19</li> <li>● Preset the station again. - 19</li> <li>● Select the <b>TUNER</b> input.</li> </ul>

**Remote control unit**

Symptom	Cause	Remedy
Remote control operation is not possible.	<ul style="list-style-type: none"> <li>Batteries are exhausted.</li> <li>The remote control unit is too far away from the main system, controlling angle is too large, or there is an obstacle in between.</li> <li>The audio cords and system control cords are not connected properly.</li> <li>The source component to be operated does not contain the tape(s) or CD.</li> <li>An attempt is made to play a tape which is being recorded in the cassette deck.</li> </ul>	<ul style="list-style-type: none"> <li>Replace with new batteries. — 10</li> <li>Operate the remote control unit within the controllable range. — 11</li> <li>Connect properly referring to "System connection". — 4</li> <li>Place the tape(s) or CD in the source component to be played.</li> <li>Wait until the recording is completed.</li> </ul>

**Memory backup function**

Please note that the following items will be deleted from this unit's memory if the power cord is disconnected from the AC outlet or the main power switch is turned off for approximately three days.

- The power setting is cleared and the power is set to OFF.
- The input selection is cleared and the TUNER input is selected.
- The volume setting is cleared and the volume is set to -80 dB.
- The receiving band setting is cleared and the FM band is selected.
- The frequency setting is cleared and 87.5 MHz is selected.
- The preset station memory is cleared.



Do not use contact cleaners because it could cause a malfunction. Be specially careful against contact cleaners containing oil, for they may deform the plastic components.

**For the U.S.A.****FCC WARNING**

This equipment may generate or use radio frequency energy. Changes or modifications to this equipment may cause harmful interference unless the modifications are expressly approved in the instruction manual. The user could lose the authority to operate this equipment if an unauthorized change or modification is made.

**NOTE:**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment may cause harmful interference to radio communications, if it is not installed and used in accordance with the instructions. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures.

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio / TV technician for help.

**For the U.S.A.****Note to CATV system installer:**

This reminder is provided to call the CATV system installer's attention to Article 820-40 of the NEC that provides guidelines for proper grounding and, in particular, specifies that the cable ground shall be connected to the grounding system of the building, as close to the point of cable entry as practical.

# Specifications (for U.S.A and Canada)

KR-200HT (En/K)

**⚠ Caution : Read this page carefully to ensure safe operation.**

## Audio section

Rated power output at the STEREO operation

110 watts per channel minimum RMS, both channels driven at 8  $\Omega$ , from 40 Hz to 20,000 Hz with no more than 0.8 % total harmonic distortion. (FTC)

Power output at the SURROUND operation

Front

110 watts per channel minimum RMS, both channels driven, at 8  $\Omega$ , 1 kHz with no more than 0.8 % total harmonic distortion.

Center

110 watts minimum RMS at 8  $\Omega$ , 1 kHz with no more than 0.8 % total harmonic distortion.

Surround

110 watts per channel minimum RMS, at 8  $\Omega$ , 1 kHz with no more than 0.8 % total harmonic distortion.

Total harmonic distortion ..... 0.3 % (1 kHz, 55 W, 8  $\Omega$ )

Signal to noise ratio (IHF'66)

PHONO (MM) ..... 75 dB

LINE (CD) ..... 93 dB

Input sensitivity / impedance

PHONO (MM) ..... 3.0 mV / 47 k $\Omega$

CD ..... 220 mV / 47 k $\Omega$

Tone controls

BASS .....  $\pm 8$  dB (at 100 Hz)

MIDDLE .....  $\pm 8$  dB (at 900 Hz)

TREBLE .....  $\pm 8$  dB (at 10 kHz)

N.B. circuit ..... + 5 dB (80 Hz)

Output level / impedance

Sub woofer preout ..... 2.0 V / 600  $\Omega$

## Video section

VIDEO inputs / outputs (Composite) ..... 1 Vp-p / 75  $\Omega$

## FM Tuner section

Tuning frequency range ..... 87.5 MHz ~ 108 MHz

Usable sensitivity

MONO ..... 1.3  $\mu$ V (at 75  $\Omega$ ) / 13.2 dBf  
(75 kHz dev., SINAD 30 dB)

50 dB quieting sensitivity

STEREO ..... 31.6  $\mu$ V (at 75  $\Omega$ ) / 41.2 dBf

Total harmonic distortion (1 kHz)

MONO ..... 0.5 % (65 dBf input)

STEREO ..... 0.6 % (65 dBf input)

Signal to noise ratio (1 kHz 75 kHz dev.)

MONO ..... 75 dB (65 dBf input)

STEREO ..... 68 dB (65 dBf input)

Stereo separation (1 kHz) ..... 40 dB

Selectivity (IHF  $\pm 400$  kHz) ..... 66 dB

Frequency response ..... 30 Hz ~ 15 kHz, + 0.5 dB, - 3.0 dB

## AM Tuner section

Tuning frequency range ..... 530 kHz ~ 1,700 kHz

Usable sensitivity (30 % mod., S/N 20 dB)

..... 15  $\mu$ V / (500  $\mu$ V / m)

Signal to noise ratio (30 % mod., 1 mV input) ..... 48 dB

## General

Power consumption ..... 2.8 A

**⚠ AC outlet**

SWITCHED ..... 1: (50 W, 0.42 A max.)

Dimensions ..... W: 440 mm (17-5/16")

H: 127 mm (5")

D: 389 mm (15-5/16")

Weight (net) ..... 9.0 kg (19.9 lb)



1. KENWOOD follows a policy of continuous advancements in development. For this reason specifications may be changed without notice.
2. Full performance may not be exhibited in extremely cold locations (below 0 deg.C).

# Specifications (for other countries)

KR-200HT (En/K)

**⚠ Caution : Read this page carefully to ensure safe operation.**

## Audio section

**Rated power output at the STEREO operation**

100 watts per channel minimum RMS, both channels driven at 8  $\Omega$ , from 40 Hz to 20,000 Hz with no more than 0.7 % total harmonic distortion. (FTC)

1 kHz, 10 % THD at 8  $\Omega$  ..... 120 W + 120 W (DIN/IEC) from 63 Hz to 12,500 Hz,

0.7 % T.H.D., at 8  $\Omega$  ..... 100 W + 100 W

**Power output at the Surround operation**

Front (1 kHz, 0.7 % T.H.D. at 8  $\Omega$ ) ..... 100 W + 100 W

Center (1 kHz, 0.7 % T.H.D. at 8  $\Omega$ ) ..... 100 W

Surround (1 kHz, 0.7 % T.H.D. at 8  $\Omega$ ) ..... 100 W

Front (1 kHz, 10 % T.H.D. at 8  $\Omega$ ) ..... 120 W + 120 W

Center (1 kHz, 10 % T.H.D. at 8  $\Omega$ ) ..... 120 W

Surround (1 kHz, 10 % T.H.D. at 8  $\Omega$ ) ..... 120 W

Total harmonic distortion (1 kHz, 8  $\Omega$ ) ..... 0.3 % at 50 W

**Signal to noise ratio (IHF'66)**

PHONO (MM) ..... 75 dB

CD ..... 93 dB

**Input sensitivity / impedance**

PHONO (MM) ..... 3.0 mV / 47 k $\Omega$

CD ..... 220 mV / 47 k $\Omega$

**Output level / impedance**

Sub woofer preout ..... 2.0 V / 600  $\Omega$

**Tone controls**

BASS .....  $\pm 8$  dB (at 100 Hz)

MIDDLE .....  $\pm 8$  dB (at 900 Hz)

TREBLE .....  $\pm 8$  dB (at 10 kHz)

N.B. circuit ..... + 5 dB (80 Hz)

## Video section

VIDEO inputs / outputs (Composite) ..... 1 Vp-p / 75  $\Omega$

## FM Tuner section

Tuning frequency range ..... 87.5 MHz~108 MHz

**Usable sensitivity**

MONO ..... 2.0  $\mu$ V (at 75  $\Omega$ ) / 17.2 dBf  
(75 kHz dev., SINAD 30 dB)

**50 dB quieting sensitivity**

STEREO ..... 35  $\mu$ V (at 75  $\Omega$ ) / 42.2 dBf

**Total harmonic distortion (1 kHz)**

MONO ..... 0.7 % (65 dBf input)

STEREO ..... 0.8 % (65 dBf input)

**Signal to noise ratio (1 kHz 75 kHz dev.)**

MONO ..... 73 dB (65 dBf input)

STEREO ..... 66 dB (65 dBf input)

**Selectivity (IHF  $\pm$  400 kHz)** ..... 50 dB

**Stereo separation (1 kHz)** ..... 40 dB

**Frequency response** ..... 30 Hz ~ 15 kHz, + 0.5 dB, - 3.0 dB

## AM Tuner section

**Tuning frequency range**

9 kHz ..... 531 kHz ~ 1,602 kHz

10 kHz ..... 530 kHz ~ 1,610 kHz

**Usable sensitivity (30 % mod., S/N 20 dB)**

..... 13  $\mu$ V / (500  $\mu$ V / m)

**Signal to noise ratio (30 % mod., 1 mV input)** ..... 50 dB

## General

**Power consumption** ..... 250 W

**⚠ AC outlet**

SWITCHED ..... 1 : (50 W max.)

**Dimensions** ..... W: 440 mm

H: 127 mm

D: 389 mm

**Weight (net)** ..... 9.0 kg



1. KENWOOD follows a policy of continuous advancements in development. For this reason specifications may be changed without notice.
2. Full performance may not be exhibited in extremely cold locations (below 0 deg C).

---

# KENWOOD

***For your records***

Record the serial number, found on the back of the unit, in the spaces designated on the warranty card, and in the space provided below. Refer to the model and serial numbers whenever you call upon your dealer for information or service on this product.

Model \_\_\_\_\_ Serial Number \_\_\_\_\_